

BNC Dual video Terminal Board

TY-FB9BD

Product summary

1-slot width video terminal board with 2 independent inputs (Composite and S-Video).

Product specification (Design and specifications subject to change without notice)

| Slot Compatibility | | | | | | | | |
|----------------------|--|--|-------------------------|------------------------------|-----------------------|-----------------------|-----------------------|-----------------------|
| 2 slot model | Slot 1, Slot 2 | | | | | | | |
| 3 slot model | Slot 1, Slot 2 (Slot 3 is not compatible) | | | | | | | |
| INPUT / OUTPUT | | | | | | | | |
| VIDEO IN | BNC x 1 1.0 Vp-p / 75 Ω | | | | | | | |
| AUDIO IN (L/R) | RCA pin jack x 2 0.5 Vrms | | | | | | | |
| S-VIDEO IN | S-VIDEO x 1 Y : 1.0 Vp-p / 75 Ω C: 0.286 Vp-p / 75 Ω (NTSC) C: 0.3 Vp-p / 75 Ω (PAL) | | | | | | | |
| AUDIO IN (L/R) | RCA pin jack x 2 0.5 Vrms | | | | | | | |
| Signals table | | | | | | | | |
| | Signal | Horizontal frequency (kHz) | Vertical frequency (Hz) | Colour System Setting on OSD | | | | |
| | | | | AUTO | NTSC | PAL | SECAM | M.NTSC |
| 1 | NTSC | 15.734 | 59.94 | <input type="radio"/> | <input type="radio"/> | | | |
| 2 | PAL | 15.625 | 50.00 | <input type="radio"/> | | <input type="radio"/> | | |
| 3 | PAL60 | 15.734 | 59.94 | <input type="radio"/> | | <input type="radio"/> | | |
| 4 | PAL-M | 15.734 | 59.94 | <input type="radio"/> | | <input type="radio"/> | | |
| 5 | PAL-N | 15.625 | 50.00 | <input type="radio"/> | | <input type="radio"/> | | |
| 6 | SECAM | 15.625 | 50.00 | <input type="radio"/> | | | <input type="radio"/> | |
| 7 | M. NTSC | 15.734 | 59.94 | <input type="radio"/> | | | | <input type="radio"/> |
| Weight | | approx. 250 g (0.55 lbs) | | | | | | |
| Included Accessories | | Terminal function label x 1 Screw x 4 Terminal board replacement instructions | | | | | | |

Dimensions

Units : mm (inch)

